



VHF AND UHF TRANSCEIVERS

IC-F14

(VHF transceiver, rotary type)

IC-F24

(UHF transceiver, rotary type)

IC-F14S

(VHF transceiver, toggle type)

IC-F24S

(UHF transceiver, toggle type)



Basic & Rugged



16ch (F14/F24)
Max. 4ch (F14S/F24S)

2-Tone, 5-Tone
CTCSS, DTCS

MDC PTT ID &
MDC emergency call

15-16 hrs. operating
time with BP-232N

Optional voice
scrambler

Built to last, built to work!



The IC-F14/S series shows Icom's sign. Simple operation for everyone for your daily business. Its very durable, shock and vibration. The dual rail battery pack to the radio. Wide range battery pack, loud and clear audio unit connector combined with Icom the IC-F14/S series will easily exc



Tough and reliable construction

The IC-F14/S series is built around an aluminum die-cast chassis and covered with tough polycarbonate casing. This radio is built to last. Its dual slide rail securely locks the battery to the radio. The battery terminal is covered with a non-corrosive rubber packing. The belt clip is clamped between the radio and the battery, making it nearly impossible to knock loose.

Simple operation

Having only 3 buttons, volume and channel knobs, the IC-F14/S series does not require special training to use. Positive button action for sure operation even when wearing gloves, allows you to get down to the business of communicating without fuss.

Wide frequency coverage

The IC-F14/S series covers a wide frequency range with one version (136–174, 400–470, 450–512 (520) MHz). Wide and narrow channel spacing (25, 12.5kHz) is programmable per channel.

VHF TRANSCEIVERS

IC-F14

IC-F14S

UHF TRANSCEIVERS

IC-F24

IC-F24S



Its new direction in LMR radio define a powerful and reliable tool. Durable construction is resistant to all guide design securely locks the wide range frequency coverage, Li-Ion radio, built-in signalings and option from grade electrical performance, meet your expectations.

Lithium-Ion battery standard

The IC-F14/S series comes with a high capacity 2000mAh Li-Ion battery pack, BP-232N, as standard. Li-Ion batteries have virtually no memory issues and allows you flexible charging.

Optional board

The IC-F14/S series has an expansion socket for adding an optional board. Voice scrambler, man down and DTMF decoder features are available, depending on the installed board.

Most popular signalings built-in

Use the built-in 2-Tone, 5-Tone, CTCSS and DTCS capabilities as standard to set up your own talk groups and quiet stand-by when others are talking.

Multiple 2-Tone, Multiple 5-Tone

Up to 10 2-Tone/8 5-Tone codes can be decoded on a channel. When a matched tone is received, the following items are programmable for each code.

- Beep sound • Answer back • Stun
- LED blink • Scan

Other features

- MDC PTT ID and MDC emergency call functions are available (Transmit only)
- LED low battery alert
- TOT function and lock out penalty timer
- 2 step power saver
- Normal and priority scan
- 500mW loud and clear audio
- Optional VOX headset
- PC programming capability

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

BATTERY PACKS AND CASE



▲ BP-230N



▲ BP-232N



▲ BP-240

Battery packs	Type and capacity	Operating time* (VHF/UHF)	Output power (VHF/UHF)
BP-230N	Li-Ion 7.4V/ 980mAh	7.35 hours	5W/4W
BP-232N	Li-Ion 7.4V/2000mAh	16/15 hours	5W/4W
BP-240	AAA (LR03) batteries × 6	—	1W

* Operating time is approximate time (at 20°C). Tx: Rx: standby=5:5:90. Power save on.

REGULAR CHARGER



▲ BC-147

▲ BC-171

BC-171 DESKTOP CHARGER + BC-147 AC ADAPTER
Charges the BP-232N in 10 hours (approx.).

RAPID CHARGER



▲ BC-145

BC-160 DESKTOP CHARGER + BC-145 AC ADAPTER
Charges the BP-232N in 3 hours (approx.).
BC-119N + AD-106 + BC-145 is also available. : Charges the BP-232N in 3 hours (approx.).

POWER SUPPLY CABLES



▲ CP-17L

▲ OPC-515L

CP-17L CIGARETTE LIGHTER CABLE, OPC-515L DC POWER CABLE
For use with the BC-160 or BC-119N. (12–16V DC required).

MULTI-CHARGER



▲ BC-121N+AD-106 (6 pcs.)

▲ OPC-656

▲ BC-157

BC-121N MULTI-CHARGER + AD-106 CHARGER ADAPTER + BC-157 AC ADAPTER (Six AD-106s are required)
Charges up to 6 battery packs in 3 hours (approx.) when BP-232N is attached.
OPC-656 DC POWER CABLE : For use with the BC-121N. (12–20V DC required).

BELT CLIPS AND LEATHER BELT HANGERS



▲ MB-93

▲ MB-96F

MB-93 : Swivel type belt clip.
MB-94 : Alligator type. Same as supplied.
MB-96N : Swivel type belt hanger.
MB-96F : Fixed type belt hanger.

HEADSETS and PTT/VOX UNIT



▲ HS-95

▲ VS-1L

▲ HS-94

▲ HS-97

HS-94 : Earhook headset with flexible boom microphone.
HS-95 : Behind-the-head headset with flexible boom microphone.
HS-97 : Throat microphone fits around your neck and picks up speech vibration.
VS-1L : PTT/VOX unit. Required when using these headsets with the transceiver.

SPEAKER-MICROPHONES



▲ HM-153L

HM-166L ▲

▲ HM-158L

▲ HM-159L

HM-153L : Durable earphone-microphone with revolving clip.
HM-158L : Compact and durable body with plug screw connector.
HM-159L : Full size durable speaker microphone.
HM-166L : Light-weight earphone microphone with revolving clip.
SP-13 : EARPHONE Provides clear audio in noisy environments.

INTERNAL UNITS



UT-108
DTMF DECODER



UT-109 VOICE
SCRAMBLER UNIT



UT-110 VOICE
SCRAMBLER UNIT



UT-124 MAN
DOWN UNIT

UT-108 : Provides DTMF, Selective call and ANI capabilities.
UT-109 : Up to 32 scrambling codes are available. Version 01 is required.
UT-110 : Up to 1020 scrambling codes are available. Version 01 is required.
UT-124 : Automatically sends an emergency signal when the transceiver is left in a horizontal position for a preset time.

STUBBY ANTENNAS

- FA-SC56VS : 150–162MHz
- FA-SC57VS : 160–174MHz
- FA-SC73US : 450–490MHz

CUT ANTENNAS

- FA-SC61VC : 136–174MHz
 - FA-SC61UC : 380–520MHz
- Cut the antenna element to tune to a specific center frequency.

ANTENNAS

- FA-SC25V : 136–150MHz
- FA-SC55V : 150–174MHz
- FA-SC25U : 400–430MHz
- FA-SC57U : 430–470MHz
- FA-SC72U : 470–520MHz

SPECIFICATIONS

GENERAL	
• Frequency range	:
IC-F14/IC-F14S	136–174MHz (U.S.A. and General)
IC-F24/IC-F24S	400–470MHz (U.S.A. and General)
	450–512MHz (U.S.A.)
	450–520MHz (General)
• Number of channels	:
	16 (IC-F14, IC-F24)
	4 (Max., IC-F14S, IC-F24S)
• Channel spacing	:
	12.5kHz/25kHz
• PLL channel step	:
	2.5kHz, 3.125kHz (VHF)
	5kHz, 6.25kHz (UHF)
• Power supply requirement	: 7.2V DC
• Current drain (at 7.2V DC; approx.):	
Transmit High	1.5A
Low (1W)	0.7A
Receive stand-by	70mA
rated output	300mA
• Antenna impedance	: 50Ω
• Usable temperature range	: –30°C to +60°C; –22°F to +140°F
• Dimensions (with BP-232N):	53 (W) × 120 (H) × 42.4 (D) mm;
(projections are not included)	$2\frac{3}{32}$ (W) × $4\frac{23}{32}$ (H) × $1\frac{21}{32}$ (D) in
• Weight	: 296g; 10.4oz (approx. with BP-232N)

TRANSMITTER	
• Output power	: 5W (VHF), 4W (UHF)
• Max. frequency deviation	: ±5.0/2.5kHz (Wide/narrow)
• Frequency error	: ±2.5ppm
• Spurious emissions	: 80dB typ.
• Adjacent channel power	:
VHF	80/70dB typ. (Wide/narrow)
UHF	75/68dB typ. (Wide/narrow)
• FM Hum and Noise	: 46dB typ. (Wide)
	40dB typ. (Narrow)
• Audio harmonic distortion	: 3% typ. (AF 1kHz, 40% deviation)
• Modulation limiting	: 60–100% of max. deviation
• Ext. microphone connector	: 3-conductor 2.5 (d) mm ($\frac{1}{16}$ ")/2.2kΩ

Measurements made in accordance with EIA/TIA-603. All stated specifications are subject to change without notice or obligation.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia and/or other countries.

RECEIVER	
• Sensitivity	: 0.25μV typ. (at 12dB SINAD)
• Squelch sensitivity	: 0.25μV typ. (at threshold)
• Adjacent channel selectivity	: 75dB typ. (Wide)
	65dB typ. (Narrow)
• Spurious response	: 70dB
• Intermodulation	: 74dB typ.
• Hum and noise ratio	: 50dB typ. (Wide)
	45dB typ. (Narrow)
• Audio output power	: 500mW typ.
	(at 5% distortion with an 8Ω load)
• External speaker connector	: 2-conductor 3.5 (d) mm ($\frac{1}{8}$ ")/8Ω

Applicable U.S. Military Specifications

Icom makes rugged products that have been tested to and passed the following MIL-STD requirements and strict environmental standards.

Standard	MIL 810F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4-3	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

SUPPLIED ACCESSORIES

(May differ according to version)



Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Icom (Europe) GmbH

Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone: +49 (0211) 346047
Fax: +49 (0211) 333639
E-mail: info@icom-europe.com
URL: <http://www.icom-europe.com>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
08190, Sant Cugat del Valles, Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone: +44 (01227) 741741
Fax: +44 (01227) 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejont des Moulins, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Icom Polska

Sopot, 3 maja 54, Poland
Phone: +48 (58) 550 7135
Fax: +48 (58) 551 0484
E-mail: icompolka@icompolka.com.pl
URL: <http://www.icompolka.com.pl>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding
Road, Haidian District, Beijing, 100039, China
Phone: +86 (010) 5889 5391/5392/5393
Fax: +86 (010) 5889 5395
E-mail: bjicom@bjicom.com
URL: <http://www.bjicom.com>

Your local distributor/dealer:

American Communication Systems

Discover the Power of Communications™

TO ORDER – VISIT <http://www.ameradio.com>